

ProLume

Electronic Linear Fluorescent Ballast Specifications

Ballast Type: Electronic Fluorescent

Starting Method: Instant Start

Lamp Connection: Parallel

Input Voltage: 120V

Input Frequency: 60Hz

Lamp Type	# of Lamps	Volts	Rated Lamp Watts	Min. Start Temp (°F/°C)	Input Current (Amps)	Input Power (Watts)	Ballast Factor	THD %	Power Factor	B. E. F.	Wire Diag.
F32T8	4	120	32	0/-18	1.62	103	0.82	<165	0.5	0.80	4-6
F32T8	3	120	32	0/-18	1.35	86	0.90	<170	0.5	1.04	3-9
F25T8	4	120	25	0/-18	1.25	86	0.86	<170	0.5	1.00	4-6
F25T8	3	120	25	0/-18	1.12	77	1.00	<175	0.5	1.31	3-9
F17T8	4	120	17	0/-18	0.97	67	0.95	<175	0.5	1.42	4-6
F40T8	3	120	40	32/0	1.62	101	0.87	<165	0.5	0.86	3-9

Also operates equivalent U-shaped lamps
For residential use only

WIRING DIAGRAMS

STANDARD LEAD LENGTH

	in.	cm.
Black	25	63.50
White	25	63.50
Blue	31	78.74
Red	31	78.74
Yellow	46	121.92

OCV: 600V

CASE DIAGRAM

CASE DIMENSIONS

Overall (L)	Width (W)	Height (H)	Mounting (M)
9.50"	1.30"	1.1"	8.90"

HOT SPOT LOCATION

Maximum Case Temperature: 167°F

Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.

PN# 50158

