

### ProLume ProFormance

## Electronic Linear Fluorescent Ballast Specifications

Ballast Type: Electronic Fluorescent  
 Starting Method: Instant Start  
 Lamp Connection: Parallel  
 Input Voltage: 120V  
 Input Frequency: 60Hz

Lamp Type	# of Lamps	Volts	Rated Lamp Watts	Min. Start Temp (°F/°C)	Input Current (Amps)	Input Power (Watts)	Ballast Factor	THD %	Power Factor	B. E. F.	Wire Diag.
F32T8	2	120	32	0/-18	0.49	59	0.87	<30	0.97	1.45	2-17
F32T8	1	120	32	0/-18	0.34	38	1.01	<32	0.94	2.65	1-3
F25T8	2	120	25	0/-18	0.41	47	0.85	<30	0.96	1.81	2-17
F17T8	2	120	17	0/-18	0.31	33	0.86	<35	0.90	2.59	2-17
F40T8	1	120	40	32/0	0.39	45	1.00	<30	0.96	2.22	1-3

Also operates equivalent U-shaped lamps

#### WIRING DIAGRAMS

1-3                      2-17

#### STANDARD LEAD LENGTHS

	in.	cm.
Black	25	63.50
White	25	63.50
Blue	31	78.74
Red	46	121.92

OCV: 600V

#### CASE DIAGRAM

#### CASE DIMENSIONS

Overall (L)	Width (W)	Height (H)	Mounting (M)
9.50"	1.30"	1.00"	8.90"

#### HOT SPOT LOCATION

Maximum Case Temperature: 167°F

Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.

PN# 50176

