

ProLED® Decorative Series Dimmer Compatibility

ProLED Product Code & Product Number

G25/8WW/LED (80018)	
B11CL3/827/LED (80094)	
B11CL3/827/BR/LED (80789)	B11CL3/827/CHR/LED (80790)
B11CL5/827/LED (80820)	B11CL5/827/E26/LED (80168)

Lamps per 600W Dimmer

Lamp type	Inrush	# of Lamps
G25 8W	80W	7
B11 3W	25W	24
B11 5W	50W	12

Brand	Model	Load	Type	Compatibility	Max Lamps	Compatibility	Max Lamps	Compatibility	Max Lamps
Lutron®	DVCL-153P	150W	C.L*	YES	5	N/A	N/A	YES	6
	"Lutron® C-L" ANALOG DIMMERS	150W	C.L*	YES	5	N/A	N/A	YES	6
	MRF2-3PD	300W	C.L*	YES	8	YES	12	YES	6
	PD-3PCL	100W	C.L*	YES	3	YES	9	YES	3
	DVELV-300P/SELV-300P	300W	ELV	YES	3	YES	12	YES	6
	MAELV-600/VTELV-600	600W	ELV	YES	7	YES	24	YES	12
	MRF2-6ELV	600W	ELV	YES	7	YES	24	YES	12
	NELV-450	450W	ELV	YES	5	YES	18	YES	9
	AY-600P/CN-600P/S-600P/Q-600P	600W	INC	YES	7	YES	24	YES	12
	D-600PH	600W	INC	YES	7	YES	24	YES	12
	D-603PH	600W	INC	YES	7	YES	24	YES	12
	DV-600PH/D-600PH	600W	INC	YES	7	YES	24	YES	12
	DV-603PG/TG-603PGH	600W	INC	YES	7	YES	24	YES	12
	GL-600H	600W	INC	YES	7	YES	24	N/A	N/A
	S-600P	600W	INC	YES	7	YES	24	YES	12
	TG-600PNLH	600W	INC	YES	7	YES	24	N/A	N/A
	TT-300NLH	300W	INC	YES	3	YES	12	YES	6
	AYLV-600P/DVLV-600P	600W	MLV	YES	7	YES	24	YES	12
	NTLV-600/NLV-600	600W	MLV	N/A	N/A	N/A	N/A	N/A	N/A
MRF2-6ND	600W	SMART/RF	YES	7	YES	24	YES	12	
RRD-10ND	1000W	SMART/RF	YES	12	YES	40	YES	20	
Leviton®	6613	450W	MLV	YES	5	YES	18	N/A	N/A
	6633	600W	INC	YES	7	YES	24	N/A	N/A
	6683	600W	INC	YES	7	YES	24	YES	12
	6602	600W	INC	N/A	N/A	N/A	N/A	YES	12
	6684	600W	INC	YES	7	YES	24	N/A	N/A
	RP106-LAW	600W	INC	YES	7	YES	24	YES	12
	6674	150W	CFL/LED*	YES	18	YES	42	YES	30
	IPL06	150W	CFL/LED*	YES	18	YES	42	N/A	N/A
	IPE04	300W	ELV	YES	3	YES	X	YES	6
	6615	300W	ELV	NO	X	NO	X	YES	6
	6681	600W	INC	YES	7	YES	24	YES	12
IPI06	600W	INC	YES	7	YES	24	YES	12	
Pass & Seymour®	CD703-PW	700W	INC	YES	8	YES	28	YES	14
	CDLV703-PW	700W	MLV	YES	8	YES	28	YES	14
	DCL453-PTC	450W	CFL/LED*	NO	X	NO	X	N/A	N/A
	D703-PTC	700W	INC	YES	8	YES	28	YES	14
	DRD4	600W	INC	YES	7	YES	24	YES	12
	DLV703	700W	MLV	YES	8	YES	28	YES	14

*Dimmers specifically designed for use with CFL or LED lamps neutralize the initial "Inrush Current" of each lamp. Other types of dimmers must take Inrush Current into account when calculating maximum # of lamps allowed for each dimmer.