

Halco T8 Type A 12W LED Tube Ballast Compatibility List

No.	Ballast Brand	Model No.	Start Type	Max Loading	Compatibility (Y/N)			
					1 lamp	2 lamps	3 lamps	4 lamps
1	DAMAR	1688B	Instant Start	2	Y	Y	N/A	N/A
2	EIKO	PM-2X32T8-UNV-IS	Instant Start	2	Y	Y	N/A	N/A
3	ESPEN	VE232MVHIPL	Instant Start	2	Y	Y	N/A	N/A
4	ESPEN	VE2P32MVHPPE 11080	Programmed Start	2	Y	Y	N/A	N/A
5	ESPEN	VE332MVHIPL	Instant Start	3	N	Y	Y	N/A
6	GE	GE132MAX-G-N	Instant Start	1	Y	N/A	N/A	N/A
7	GE	GE132MAXP-L/ULTRA	Instant Start	1	Y	N/A	N/A	N/A
8	GE	GE132MAXP-N/ULTRA	Instant Start	1	Y	N/A	N/A	N/A
9	GE	GE-132-MV-N	Instant Start	1	Y	N/A	N/A	N/A
10	GE	GE-132-MV-PS-L	Programmed Start	1	Y	N/A	N/A	N/A
11	GE	GE232MAX-G-N	Instant Start	2	Y	Y	N/A	N/A
12	GE	GE232MAX-G-N-DILY	Instant Start	2	Y	Y	N/A	N/A
13	GE	GE232MAXP-L/ULTRA	Instant Start	2	Y	Y	N/A	N/A
14	GE	GE-232-MV-N	Instant Start	2	Y	Y	N/A	N/A
15	GE	GE232-MVPS-L	Programmed Start	2	Y	Y	N/A	N/A
16	GE	GE232MVPSN-V03	Dimmable	2	Y	Y	N/A	N/A
17	GE	GE-232-MVPS-XL	Programmed Start	2	Y	Y	N/A	N/A
18	GE	GE332MAX-G-N	Instant Start	3	Y	Y	Y	N/A
19	GE	GE332MAX-G-N-DIYB	Instant Start	3	Y	Y	Y	N/A
20	GE	GE332MAXP-N/ULTRA	Instant Start	3	Y	Y	Y	N/A
21	GE	GE332MV-N-DIY	Instant Start	3	Y	Y	Y	N/A
22	GE	GE-332-MVPS-XL	Programmed Start	3	Y	Y	Y	N/A
23	GE	GE432MAX-G-N	Instant Start	4	N	Y	Y	Y
24	GE	GE432MAXG-N-DIYL	Instant Start	4	N	Y	Y	Y
25	GE	GE432MAX-L/Ultra	Instant Start	4	Y	Y	Y	Y
26	GE	GE432MAXP-H/ULTRA	Instant Start	4	N	N	N	Y
27	GE	GE432MAXP-L/ULTRA	Instant Start	4	Y	Y	Y	Y
28	HALCO	EP232IS/MV/HE	Instant Start	2	N	Y	N/A	N/A
29	HOWARD	EP2/32IS/MV/MC/HE	Instant Start	2	N	Y	N/A	N/A
30	HOWARD	EP4/32IS/MV/MC/HE	Instant Start	4	N	Y	Y	Y
31	HOWARD	EPL2/32IS/MV/MC/HE	Instant Start	2	Y	Y	N/A	N/A
32	HOWARD	EPL3/32IS/MV/SC/HE	Instant Start	3	N	Y	Y	N/A
33	HOWARD	EPL4/32IS/MV/MC/HE	Instant Start	4	Y	Y	Y	Y
34	KEYSTONE	KTEB-232-UV-IS-N-P	Instant Start	2	Y	Y	N/A	N/A
35	KEYSTONE	KTEB-332-UV-IS-N-P	Instant Start	3	Y	Y	Y	N/A
36	KEYSTONE	KTEB-432-UV-IS-N-P	Instant Start	4	N	Y	Y	Y
37	OSRAM SYLVANIA	QHE 2X32T8/347 ISL-SC	Instant Start	2	Y	Y	N/A	N/A
38	OSRAM SYLVANIA	QHE 4x32T8/UNV ISL-SC	Instant Start	4	Y	Y	Y	Y
39	OSRAM SYLVANIA	QHE 4x32T8/UNV ISN-SC	Instant Start	4	N	Y	Y	Y
40	OSRAM SYLVANIA	QTP 1X32T8/UNV ISN-SC	Instant Start	1	Y	N/A	N/A	N/A
41	OSRAM SYLVANIA	QTP 3X32T8/UNV ISN-SC	Instant Start	3	Y	Y	Y	N/A
42	OSRAM SYLVANIA	QTP 4X32T8/UNV ISN-SC	Instant Start	4	N	Y	Y	Y
43	PHILIPS ADVANCE	ICN-2P32-N	Instant Start	2	N	Y	N/A	N/A
44	PHILIPS ADVANCE	ICN-2P32-SC	Instant Start	2	Y	Y	N/A	N/A
45	PHILIPS ADVANCE	IOP-2P32-HL-N	Instant Start	2	N	Y	N/A	N/A
46	PHILIPS ADVANCE	IOP-2P32-LW-N	Instant Start	2	Y	Y	N/A	N/A
47	PHILIPS ADVANCE	IOP-2P32-N	Instant Start	2	Y	Y	N/A	N/A
48	PHILIPS ADVANCE	IOP-2PSP32-LW-N	Programmed Start	2	N	Y	N/A	N/A

Halco T8 Type A 12W LED Tube Ballast Compatibility List

No.	Ballast Brand	Model No.	Start Type	Max Loading	Compatibility (Y/N)			
					1 lamp	2 lamps	3 lamps	4 lamps
49	PHILIPS ADVANCE	IOP-2PSP32-N	Programmed Start	2	N	Y	N/A	N/A
50	PHILIPS ADVANCE	IOP-4P32-LW-N	Instant Start	4	Y	Y	Y	Y
51	PHILIPS ADVANCE	IOP-4PSP32-LW-SC	Programmed Start	4	Y	Y	Y	Y
52	PHILIPS ADVANCE	IOP-4PSP32-SC	Programmed Start	4	N	Y	Y	Y
53	PHILIPS ADVANCE	IOPA-1P32-LW-N	Instant Start	1	Y	N/A	N/A	N/A
54	PHILIPS ADVANCE	IOPA-2P32-LW-N	Instant Start	2	Y	Y	N/A	N/A
55	PHILIPS ADVANCE	IOPA-2P32-N	Instant Start	2	N	Y	N/A	N/A
56	PHILIPS ADVANCE	IOPA-3P32-LW-SC	Instant Start	3	Y	Y	Y	N/A
57	PHILIPS ADVANCE	IOPA-3P32-N	Instant Start	3	N	N	Y	N/A
58	PHILIPS ADVANCE	IOPA-4P32-LW-N	Instant Start	4	Y	Y	N	N
59	PHILIPS ADVANCE	IOPA-4P32-N	Instant Start	4	N	N	N	Y
60	PHILIPS ADVANCE	RCN-2S32-SC	Instant Start	2	N	Y	N/A	N/A
61	PHILIPS ADVANCE	REL-2P32-SC	Instant Start	2	N	Y	N/A	N/A
62	PHILIPS ADVANCE	REZ-2S32-SC	Dimmable	2	Y	Y	N/A	N/A
63	UNIVERSAL	B232IUNV-C	Instant Start	2	N	Y	N/A	N/A
64	UNIVERSAL	B232IUNVEL-N	Instant Start	2	Y	Y	N/A	N/A
65	UNIVERSAL	B232IUNVHP-N	Instant Start	2	Y	Y	N/A	N/A
66	UNIVERSAL	B232PUNVHE-B	Programmed Start	2	Y	Y	N/A	N/A
67	UNIVERSAL	B332IUNVEL-A	Instant Start	3	Y	Y	Y	N/A
68	UNIVERSAL	B332IUNVHE-A	Instant Start	3	Y	Y	Y	N/A
69	UNIVERSAL	B432IUNVHE-A	Instant Start	4	N	Y	Y	Y
70	UNIVERSAL	B432PUNVHE-A	Programmed Start	4	N	Y	Y	Y

Y: Compatible

N: Incompatible

N/A: Not Applicable

When working with electronic ballast please check the compatibility list first!

If you couldn't find your ballast on the list then bypass the fixture, or contact us please!

Do not install the LED tube with the ballast which is not on the ballast compatibility list, risk of firing!