



PRISM JCD G9



Technical Data

- 25, 40 and 60 watt
- Line Voltage
- 2900K
- G9 loop base for safe line-voltage applications
- High Lumen maintenance - over 90% throughout lamp life

Benefits

- User-friendly, easy to install
- Eliminates the liability of installing a 12 volt lamp into a 120 volt socket
- White light
- High lumen maintenance
- Compact light source

- » Easy to install
- » High lumen maintenance
- » White light

Markets:

- Residential
- Commercial

Applications:

- Under cabinet lighting
- Accent lighting
- Task lighting
- Display lighting

where there's light, there's halco®

Contact your account representative at 800.677.3334 for pricing, orders and technical support.

Visit us at halcolighting.com



Catalog Number: _____ Type: _____
 Project: _____
 Comments: _____ Date: _____
 Prepared By: _____

Ordering Information

Watts	Base	Product #	Product Code	Description	Volts	Lumens	Avg. Rated Life	Pkg. Qty.	Filament Design	MOL
25 Watt	G9	71001	JCD25/G9	Clear	130V	280	2000	10/500	CC-2V	1.69"
25 Watt	G9	107902	JCD25FR/G9	Clear	130V	280	2000	10/500	CC-2V	1.69"
40 Watt	G9	107902	JCD40/G9	Clear	130V	480	2000	10/500	CC-2V	1.69"
40 Watt	G9	107908	JCD40FR/G9	Clear	130V	480	2000	10/500	CC-2V	1.69"
40 Watt	G9	107310	JCD40/FR/G9/120	Clear	120V	480	2000	10/500	CC-2V	1.69"
60 Watt	G9	71002	JCD60/69	Clear	130V	780	2000	10/500	CC-2V	1.69"
60 Watt	G9	107904	JCD60FR/69	Frost	130V	780	2000	10/500	CC-2V	1.69"